

80 003 10 ECO Sirenenode

N Trådløst styrt stikkontakt for sirene

Norsk bruker- og installasjonsveiledning

Pakkens innhold

1 stk ECO Sirenenode for Schuko stikkontakt og støpsel.

Beskrivelse

Eco Sirenenode er en trådløst kontrollert stikkontakt for kontroll av sirener, lyskastere og lignende utstyr. ECO Sirenenode kontrolleres trådløst av en Sikom ECO sentral. Hvis en brann eller bevegelsesdetektor i systemet løser ut alarmen, sender sentralen signal til ECO Sirenenode.

ECO Sirenenode slår på 230VAC strømutgang hvis bevegelsesalarm eller brannalarm blir utløst. Sirenenoden kan tilkobles 230VAC varsellys, sirenløsninger eller lignende med 230VAC støpseltilkobling.

Sirenenodens strømutgang står på i 10 minutter ved utløst alarm. Deretter slås den av automatisk. Ved en eventuell ny alarm, slås utgang på i nye 10 minutter.

Slå av sirenenodens utgang

Ved bevegelsesalarm: man kan slå sirenenoden av ved å slå av alarmen i Sikom-systemet.

Ved brannalarm: Slå bevegelsesalarmen i Sikom-systemet av. NB: Brannalarmen er normalt aktiv selv om bevegelsesalarmen er av. Hvis bevegelsesalarmen allerede er av, slå den PÅ, deretter AV.

Innganger på sirenenode

ECO Sirenenode har to RJ-45 innganger. Disse inngangene er ikke i bruk på ECO Sirenenode. Temperaturfølere eller annet utstyr skal ikke kobles til.

Trådløs rekkevidde

Produktet har en trådløs rekkevidde for fjernstyring på opp mot 60 m i fri sikt. Tykke vegger og etasjeskiller av tre og betong vil redusere rekkevidden. Rekkevidde i et hus vil normalt være maks.15 meter.

Montering

ECO Sirenenode plugges inn i stikkontakt. Tilbehør som skal slås på ved alarm, kobles inn i sirenenodens strøm-utgang.

Innmelding mot sentral

1. Ta ECO Sirenenode ut av stikkontakt.
2. Aktiver innmelding på Sikom -sentralen. Se sentralens manual for hvordan dette gjøres.
3. Innen 1 minutt, - plugg ECO Sirenenode inn i stikkontakt.

En vellykket innmelding indikerer at radiorekkevidde er tilstrekkelig. Hvis det skal meldes inn flere enheter, må hele denne prosedyren repeteres.

Garanti

Garanti betyr at Sikom Connect AS er ansvarlig for at produktet er fritt for material- og produksjonsfeil som begrenser eller umuliggjør funksjonalitet som er beskrevet for produktet. Garantien forutsetter fremvisning av originalfaktura, hvor kjøpsdato og type apparat tydelig fremgår.

Hva dekkes av garantien?

Under garantiperioden vil Sikom Connect AS etter eget valg reparere produktet eller skifte ut defekte deler med nye som tilsvare de opprinnelige i funksjon og ytelse. Dersom Sikom Connect etter gjentatte forsøk ikke er i stand til å utbedre feilen slik at produktet ikke fungerer i henhold til produktets beskrivelse, kan Sikom Connect etter eget valg refundere kjøpesummen eller erstatte produktet med et funksjonelt likeverdig produkt. Alle deler og produkter som er skiftet ut i forbindelse med garantitjenester forblir Sikom Connects eiendom.

Hva dekkes ikke av garantien?

Skader som skyldes bruk utenfor de driftsparametere som er oppgitt i manualene. Funksjonssvikt forårsaket av transportskade. Service eller modifikasjoner utført av andre enn Sikom Connect. Feil som skyldes bruk av deler som ikke er beregnet for produktet. Skader som skyldes eksterne faktorer, som lynnedslag, feil strømtilførsel, feil i mobilnettet, vannskader eller brann. Montasje som ikke følger gjeldende installasjonskrav. Hvis serienummeret er endret, fjernet eller ikke er lesbart.

Tekniske spesifikasjoner:

Produsent: Sikom Connect AS, Norway
Artikkelnavn ECO Sirenenode
Artikkelnummer:..... 80 003 10
Modellnummer..... 300-8306V20
Driftstemperatur:..... -20 C til +50 C
Driftsspennning:.....230 VAC
Radio:..... 433.9 MHz , 10mW
Maksimal belastning utgang..... 16A resistiv last
Godkjenning..... CE
Sikom Connect AS erklærer at ECO Sirenenode er i overensstemmelse med direktiv 2014/53/EU. Samsvarserklæringen i fulltekst er tilgjengelig på følgende internettadresse: www.sikom.no

Kontaktinformasjon:

Sikom Connect AS	Phone: +47 740 85 960
	E-mail: post@sikom.no
7010, Trondheim, Norway	Web: www.sikom.no



80 003 10 ECO Sirenenode

GB Wireless controlled socket plug for siren

English installation and user manual

Package contents

1 pc ECO Siren node for Schuko type socket and plug

Description

Eco Sirenenode is a wireless controlled socket plug for controlling power to sirens, floodlights or similar equipment.

ECO Sirenenode is wirelessly controlled by a Sikom ECO gateway. If a fire or burglar detector in the system triggers the alarm, the Sikom gateway sends a signal to the ECO Sirenenode.

ECO Sirenenode is plugged into a schuko 230VAC power outlet. It switches on its 230VAC output if a burglar alarm or fire alarm is triggered in the Sikom system.

ECO Sirenenode output can be connected to 230VAC flood lights, sirens or the like using a 230VAC Schuko connector.

The power output is switched on for 10 minutes if an alarm is triggered. Then it switches off automatically.

In the event of a new alarm, the output is switched on for another 10 minutes.

Switch off power output

In case of a burglar alarm: ECO Sirenenode output can be switched off by turning off the burglar alarm in the Sikom system.

In case of a fire alarm: Turn off the burglar alarm in the Sikom system. The ECO Sirenenode output switches off.

Note: The fire alarm is normally active even if the burglar alarm is turned off.

If the burglar alarm is already off, turn it ON, then OFF.

ECO Sirenenode inputs

ECO Sirenenode has two RJ-45 inputs.

These inputs are not used. Temperature sensors or other equipment must not be connected.

Wireless range

In general: Wireless range between ECO Sirenenode and the Sikom ECO gateway is about 60 meters in line of sight. Walls, ceilings, floors and other obstacles will reduce the range. Massive timber and concrete are examples of materials that will limit the wireless range. Wireless range in a regular timber frame building is usually max. 15 meters.

Position the Sikom gateway centrally / within wireless range of the ECO Sirenenode.

Installation

The ECO Sirenenode is plugged into a wall socket. Accessory to be switched on by the alarm is connected to the 230VAC output.

Registration with a Sikom gateway

1. First, unplug ECO Sirenenode from power outlet.
2. Activate the registration procedure on the Sikom gateway.
Read the user manual for your Sikom gateway to find the correct procedure.
3. Within 1 minute, - plug the ECO Sirenenode into power outlet.

Successful registration indicates that wireless range is ok.

To register additional units, repeat procedure for each one.

Warranty

Sikom Connect AS products are covered by a two year warranty against any faults due to material flaws or manufacturing errors, which limit or render useless certain functions described for the product. The warranty requires the customer to present the original receipt, with date of purchase and type of equipment clearly readable.

What is covered by the warranty?

During the warranty period, Sikom Connect AS. reserves the right to repair the product or to replace defective parts with functionally equivalent parts. If, after several attempts, Sikom Connect AS is unable to correct the problem, and the product does not work as described in the manual,

Sikom Connect may elect to refund the purchase price or to replace the product with a functionally equivalent one. All replaced parts and products become the property of Sikom Connect AS.

What is not covered by the warranty?

Indirect damage to life, health, property, revenue and environment caused by circuits and appliances connected to the units (install and use this product responsibly). Costs related to (re)installing, transporting and dismantling units; recycling may be governed by special rules. Damages caused by use outside of the operating conditions specified in the manual. Malfunctions caused by transport damages, any unauthorized repair, modification or disassembly. Use of non-original parts. External factors, such as lightning, power supply issues, mobile network issues, flood damage or fire. Units with modified, removed or unreadable serial number.

Technical specifications:

Manufacturer:..... Sikom Connect AS, Norway
Article nameECO Sirenenode
Article Number.....80 003 10
Model number.....300-8306V20
Operating temperature:..... - 20 C to +50 C
Power supply:..... 230 VAC
Radio:.....433.9 MHz , 10mW
Max load:..... 16A resistive load
Approval:..... CE
Hereby, Sikom Connect AS declares that the radio equipment type ECO Sirenenode is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address: www.sikom.no

Contact information

Sikom Connect AS Phone: +47 740 85 960
E-mail: post@sikom.no
7010, Trondheim, Norway Web: www.sikom.no

